

Husqvarna DM 340

Powerful electric core drill for use with stand. DM 340 is the perfect choice for medium and heavy core drilling where high production rates are needed, especially with large diameter core bits. Recommended diameter up to 400 mm. The motor is very easy to operate with several ergonomic features facilitating drilling and set up. Suitable for water evacuation, ventilation, angle drilling and stitch drilling.

- ⊙ Drill bit diameter with stand, max **400 mm**
- ⚡ Voltage **220-240 V**

Article number : DRILL MOTOR DM 340 220-240 V | 1-ph | 50 Hz | EU | 11/4" 7 - 965 9872-07



FEATURES

Want to take a closer look? Learn more about the product in depth by exploring its features and benefits.



Drill with maximum pressure

A LED indicator shows the load of the machine, allowing you to always drill at maximum pressure.



Easy start with reduced speed

To facilitate making a starter hole, speed is reduced by half using the Smart Start® button.

Overload protection

Increases productivity and extends service life.

- Reliable gearbox
- Load indicator
- Elgard™
- Softstart™
- Angle drilling
- Barriers

Durable and ergonomic design

Durable and shock-proof, designed to protect the electronics. Easy to carry and install thanks to low weight and ergonomic design.

- Horizontal drilling
- Stitch drilling
- Water evacuation
- Vertical drilling
- Channels, pipes and cables

SPECIFICATIONS



Dimensions

Water connector	G 1 / 4"
Weight	14 kg
Product size length	505 mm
Product size width	142 mm



Motor

Electronic product	Yes
Frequency	50 Hz
Voltage	220-240 V
Rated input power	3.3 kW

Specifications

Water pressure, max	8 bar
Spindle thread, outer	1 1/4" 7 UNC



Drilling equipment

Drill bit diameter with stand, max	400 mm
Recommended drill bit diameter, min	50 mm



Sound and noise

Sound power level, guaranteed (LWA)	113 dB(A)
Sound power level, measured	112 dB(A)
Sound pressure level at operators ear	98 dB(A)



Transmission

Number of gearbox speeds	3
--------------------------	----------